

# Dialog 4225 Vision

System Telephone for  
MD Evolution Communication System  
Release R7.0

## Quick Reference Guide



### Enter the text guide

Menu + >> + >> + "PREFIXES"

### End a call or an operation



### Use loudspeaker and hands-free modes


Make a call without using the handset

Dial without

Answer a call without using the handset

Select Lx key flashing

Switch to hands-free



Activate/deactivate loudspeaker



Activate/deactivate mute



Pre-programmed headset mode

+ \* + 1 simultaneously +

L3 (LED on)

Headset/handset



### Make calls

By name (from key panel)

Name + enter first letter of the name + select the soft key when name is displayed

Attendant

9

External number

0 + external number

Abbreviated number

2 + abbreviated number

Redial last external Nr dialled

"REDIAL"

Using repertory key

associated to person you want to call

Avoiding receiving beeps or intrusion

>> + "PROTECT" + number you want to call

Sign-on / sign-off

>> + "SIGN-ON" + your extension number + password + + Nr you want to call

Automatic call-back

"AUTOMATIC CALLBACK" +

Intrusion

"INTRUSION"

Voice message

"VOICE PAGING"

Voice message to a group

Dial number of the group

### Answer a call

Call pick-up

"PICKUP" + number of ringing extension

Call pick-up in your principal group

"PICKUP" + "GRP\_PRI"

General ringing call pick-up

"PICKUP" + "GENERAL"

Opening the doorphone

>> + "DOOR LOCK"

### During a communication

Adjust volume of speakerphone



Identify another incoming call

Menu + flashing key

On hold

flashing key

Answer a new call

flashing key

Broker's call

flashing key

Conference

Call a 2nd person + "CONFER"

Transfer a call to another extension

Dial extension Nr +

Call park

"CALL PARK" + 2 digits code at your choice +

Retrieve a parked call

"RETRIEVE" + chosen 2-digit code

### Messages and callers file

Send a text message on not answering extension

>> + "MSG" + "DISC" + "SELECT" or "NEXT" + complete the message + "CONFIRM"

Read the callers file

"CALLERS"

**Call forwarding**

	ACTIVATION	DEACTIVATION
Immediate call forwarding	☎ Menu +“CALL FWD” + choose type of call fwd + call fwd Nr +“CONFIRM”	☎ Call fwd
Remote call forwarding	☎ Menu +“CALL FWD” +“REMOTE FWD” + yr extension Nr + choose type of call fwd + call fwd Nr + password	☎ Call fwd (from your set)
Program a registered call forwarding	☎ Menu + ☎ >> +“FIXED FWD” + choose type of call fwd + call fwd Nr +“CONFIRM”	Program another registered call forwarding
Activate call forwarding	☎ Call fwd	☎ Call fwd

**Programming your terminal**

	ACTIVATION	DEACTIVATION
Reminder	<b>71</b> + HHMM 4 digits - time of the reminder	<b>71 + 9</b>
Program dedicated repertory keys on line keys	☎ Menu + ☎ >>* + “DIRECTORY” press key to register + Nr to register + “CONFIRM” + ☎	☎ Menu + ☎ >> + “DIRECTORY” press key to register “BLANK” “CONFIRM” + ☎
Change password	<b>79</b> +old password + new password	
Lock your phone	☎ Menu + “LOCK”	☎ Menu + “LOCK”
Retrieve from «all-calls» group	☎ Menu “GROUP”	☎ Menu “GROUP”
Temporary operator	☎ Menu “GEN CALL”	☎ Menu “GEN CALL”

Choose ringing melody & adjust loudspeaker volume  
Change voice paging mode (bi-way mode)

☎ Menu  
+“RING-SPKR”  
  
☎ Menu + ☎ >>  
+ “V.PAGING”  
+“MODIFY” + ☎

**Attendant facilities**

Attendant console activation	☎ Menu + “GEN-CALL”
Attendant console deactivation / programming of extra night set	☎ Menu + “GEN-CALL” + extra night set Nr + ☎ or “CONFIRM” or “MODIFY” or “NONIGHTST”
Override of “do not disturb”	“OVERRIDE”
System call forwarding	☎ Menu + “CALL-FWD” + ☎ >> “SYSTEM” + external number (without 0)
Deactivate system call forwarding	☎ Menu + “CALL-FWD” + ☎ >> “CANC-SYST”
Call forwarding for a third party	☎ Menu + “CALL-FWD” + ☎ >> “REMOTE FWD” + number to forward + call forwarding type + forwarding Nr + your password
Programming date and time	☎ Menu + ☎ >> +“SYSTEM”+ “DATE”+ figures “CONFIRM”
Programming abbreviated number	☎ Menu + ☎ >> +“SYSTEM”+ “ABBR-NR”+ Nr of list + short number + complete number + “CONFIRM”

Initialization of pass word for an extension

☎ Menu + ☎ >> +“SYSTEM”+  
your password + ☎ >>  
+“PASSWORD”+ extension Nr +  
“CONFIRM”

Hotel facilities

See user guide for hotel console

**Declaration of Conformity**

Hereby, Aastra Telecom Sweden AB, SE-126 37 Hägersten, declares that this telephone is in conformity with the essential requirements and other relevant provisions of the R&TTE directive 1999/5/EC.

Details to be found at: <http://www.aastra.com/sdoc>



For questions regarding the product, please contact your Aastra Certified Sales Partner. Also visit us on: [www.aastra.com](http://www.aastra.com)